

## KVM-450H

Through this 16 port HDMI KVM switch can control 16 PCs via a set of keyboard, mouse and video. This KVM switch can help you to save time, money, space, device and power consumption. The item have hot-key switch, panel button method to switch. The resolution up to 4K@30Hz, Client can enjoy high visual effect.

## Features

- Support 16 HDMI computers input, 1 HDMI output
- With USB HUB interface support any USB2.0 devices
- Support Hot-swapping, no need to shut down KVM switch or computer, can plug in or out device that connected
- The resolution up to 4Kx2K@30Hz
- Switching method: hot-key and button.
- Must connect power adapter DC12V



Product Specifications	
Product Name	16 port HDMI KVM switch
Input interface	16x HDMI type A, 16x USB-B
Output interface	1x HDMI
PC select way	Hot-key, button
Resolution supported	Up to 4K*2K@ 30Hz
Keyboard simulation	USB
Mouse simulation	USB
USB2.0 device	2* USB-A
Scan time	5-199 seconds (default 5 seconds, can be set by hotkey)
Housing	Metal
Adaptor	DC12V

### Packing List:

1x 16 port HDMI KVM switch  
1x Power adapter  
1x User manual  
4x 1.5m HDMI KVM cables  
8x 1.8m HDMI KVM cables  
4x 2.5m HDMI KVM cables  
1x Rack mount  
1x IR Remote